



S112A AMPLIFIER FOR ON/OFF SENSORS - UNIVERSAL INPUT INCORPORATED PULSES DIVIDER - RELAY OUTPUT

S112A is an amplifier for ON/OFF sensors with the following features :

- **Inputs:** optoisolated to receive signals from sensors : reed (contact), NPN 2 wires, NPN 3 wires 24Vdc and 12Vdc , PNP 2 wires, PNP 3 wires 24Vdc, Namur sensor 8Vdc, photoelectric sensor.
Max frequency 400Hz, pulse min 2ms.
- **Divider:** you can divide pulses in input by a programmable factor from 1 to 256 by 8 DIP-switches.
- **Output:** one relay with SPDT switch 5A 250Vac (resistive load).
Relay's mechanical life 10.000.000 operations.
- **Warning:** green LED RETE : equipment on;
red LED USCITA : pulse's output.
- **Temperature:** -20 / +60 °C.
- **Humidity:** 40 % at 40 °C (not condensing).
- **Box:** 3 modules DIN 46277, in gray autoextinguishing noryl , to be coupled on 35mm bar.
- **Size:** 52,5 x 90 x 71 mm.
- **Weight:** 200 g approx.
- **Power:** 115 / 230 Vac +/- 10 % 50 / 60 Hz.
- **Consumption:** 1,5 VA.




Equipments complying the electromagnetic compatibility prescriptions based on the 89/366/EEC directive.


Reference norms:

- EN50081-2 : Industry environment emission norm
- EN50082-2 : Industry environment immunity norm


POWER




OUTPUT




INPUTS




NPN (2 wires)




NPN (3 wires) 24Vdc




NPN (3 wires) 12Vdc




CONTACT (REED)




NAMUR




PULSES 24Vdc



PNP (2 wires)



PNP (3 wires) 24Vdc



PHOTOELECTRIC

SPECIFIC SENSORS

Flow meters Hall effect AICHI type to be used in "NPN (3 wires) 12V" connection:


- | | | | |
|-----------|-----------|-----------------|-------------|
| - OF type | Red --> 9 | White --> 7 | Black --> 8 |
| - ND type | Red --> 9 | White+Blu --> 7 | Black --> 8 |

Contatori con emettitore di impulsi FOTOELETTRICO "ASTRA CONTATORI" :

- | | | |
|-------------|-------------|-------------|
| Brown --> 9 | Green --> 6 | White --> 5 |
|-------------|-------------|-------------|

HOW TO INSERT DIVISION'S FACTOR

To insert pulses' divider remove upper panel, replace the jumper as shown in picture and prearrange DIP-switches as indicated in table:



HOW TO PROGRAM DIVIDER (0 = DIP-switch in OFF, 1 = DIP-switch in ON)

n	1	2	3	6	7	8	n	1	2	3	4	5	6	7	8	n	3	4	5	6	7	8	n	1	2	3	4	5	6	7	8
2	1	0	0	0	0	0	65	0	0	0	0	0	0	1	0	129	0	0	0	0	0	1	193	0	0	0	0	0	0	1	1
3	0	1	0	0	0	0	66	1	0	0	0	0	0	1	0	130	0	0	0	0	0	1	194	1	0	0	0	0	0	1	1
4	1	1	0	0	0	0	67	0	1	0	0	0	0	1	0	131	0	0	0	0	0	1	195	0	1	0	0	0	0	1	1
5	0	0	1	0	0	0	68	1	1	0	0	0	0	1	0	132	0	0	0	0	0	1	196	1	1	0	0	0	0	1	1
6	1	0	1	0	0	0	69	0	0	1	0	0	0	1	0	133	1	0	0	0	0	1	197	0	0	1	0	0	0	1	1
7	0	1	1	0	0	0	70	1	0	1	0	0	0	1	0	134	1	0	0	0	0	1	198	1	0	1	0	0	0	1	1
8	1	1	1	0	0	0	71	0	1	1	0	0	0	1	0	135	1	0	0	0	0	1	199	0	1	1	0	0	0	1	1
9	0	0	0	0	0	0	72	1	1	1	0	0	0	1	0	136	1	0	0	0	0	1	200	1	1	1	0	0	0	1	1
10	1	0	0	0	0	0	73	0	0	0	1	0	0	1	0	137	0	1	0	0	0	1	201	0	0	0	1	0	0	1	1
11	0	1	0	0	0	0	74	1	0	0	1	0	0	1	0	138	0	1	0	0	0	1	202	1	0	0	1	0	0	1	1
12	1	1	0	0	0	0	75	0	1	0	1	0	0	1	0	139	0	1	0	0	0	1	203	0	1	0	1	0	0	1	1
13	0	0	1	0	0	0	76	1	1	0	1	0	0	1	0	140	0	1	0	0	0	1	204	1	1	0	1	0	0	1	1
14	1	0	1	0	0	0	77	0	0	1	1	0	0	1	0	141	1	1	0	0	0	1	205	0	0	1	1	0	0	1	1
15	0	1	1	0	0	0	78	1	0	1	1	0	0	1	0	142	1	1	0	0	0	1	206	1	0	1	1	0	0	1	1
16	1	1	1	0	0	0	79	0	1	1	1	0	0	1	0	143	1	1	0	0	0	1	207	0	1	1	1	0	0	1	1
17	0	0	0	0	0	0	80	1	1	1	1	0	0	1	0	144	1	1	0	0	0	1	208	1	1	1	1	0	0	1	1
18	1	0	0	0	0	0	81	0	0	0	0	1	0	1	0	145	0	0	1	0	0	1	209	0	0	0	0	1	0	1	1
19	0	1	0	0	0	0	82	1	0	0	0	1	0	1	0	146	0	0	1	0	0	1	210	1	0	0	0	1	0	1	1
20	1	1	0	0	0	0	83	0	1	0	0	1	0	1	0	147	0	0	1	0	0	1	211	0	1	0	0	1	0	1	1
21	0	0	1	0	0	0	84	1	1	0	0	1	0	1	0	148	0	0	1	0	0	1	212	1	1	0	0	1	0	1	1
22	1	0	1	0	0	0	85	0	0	1	0	1	0	1	0	149	1	0	1	0	0	1	213	0	0	1	0	1	0	1	1
23	0	1	1	0	0	0	86	1	0	1	0	1	0	1	0	150	1	0	1	0	0	1	214	1	0	1	0	1	0	1	1
24	1	1	1	0	0	0	87	0	1	1	0	1	0	1	0	151	1	0	1	0	0	1	215	0	1	1	0	1	0	1	1
25	0	0	0	0	0	0	88	1	1	1	0	1	0	1	0	152	1	0	1	0	0	1	216	1	1	1	0	1	0	1	1
26	1	0	0	0	0	0	89	0	0	0	1	1	0	1	0	153	0	1	1	0	0	1	217	0	0	0	1	1	0	1	1
27	0	1	0	0	0	0	90	1	0	0	1	1	0	1	0	154	0	1	1	0	0	1	218	1	0	0	1	1	0	1	1
28	1	1	0	0	0	0	91	0	1	0	1	1	0	1	0	155	0	1	1	0	0	1	219	0	1	0	1	1	0	1	1
29	0	0	1	0	0	0	92	1	1	0	1	1	0	1	0	156	0	1	1	0	0	1	220	1	1	0	1	1	0	1	1
30	1	0	1	0	0	0	93	0	0	1	1	1	0	1	0	157	1	1	1	0	0	1	221	0	0	1	1	1	0	1	1
31	0	1	1	0	0	0	94	1	0	1	1	1	0	1	0	158	1	1	1	0	0	1	222	1	0	1	1	1	0	1	1
							95	0	1	1	1	1	0	1	0	159	1	1	1	0	0	1	223	0	1	1	1	1	0	1	1

32	1 1 1 1 1 0 0 0	96	1 1 1 1 1 0 1 0	160	1 1 1 1 1 0 0 1	224	1 1 1 1 1 0 1 1
33	0 0 0 0 0 1 0 0	97	0 0 0 0 0 1 1 0	161	0 0 0 0 0 1 0 1	225	0 0 0 0 0 1 1 1
34	1 0 0 0 0 1 0 0	98	1 0 0 0 0 1 1 0	162	1 0 0 0 0 1 0 1	226	1 0 0 0 0 1 1 1
35	0 1 0 0 0 1 0 0	99	0 1 0 0 0 1 1 0	163	0 1 0 0 0 1 0 1	227	0 1 0 0 0 1 1 1
36	1 1 0 0 0 1 0 0	100	1 1 0 0 0 1 1 0	164	1 1 0 0 0 1 0 1	228	1 1 0 0 0 1 1 1
37	0 0 1 0 0 1 0 0	101	0 0 1 0 0 1 1 0	165	0 0 1 0 0 1 0 1	229	0 0 1 0 0 1 1 1
38	1 0 1 0 0 1 0 0	102	1 0 1 0 0 1 1 0	166	1 0 1 0 0 1 0 1	230	1 0 1 0 0 1 1 1
39	0 1 1 0 0 1 0 0	103	0 1 1 0 0 1 1 0	167	0 1 1 0 0 1 0 1	231	0 1 1 0 0 1 1 1
40	1 1 1 0 0 1 0 0	104	1 1 1 0 0 1 1 0	168	1 1 1 0 0 1 0 1	232	1 1 1 0 0 1 1 1
41	0 0 0 1 0 1 0 0	105	0 0 0 1 0 1 1 0	169	0 0 0 1 0 1 0 1	233	0 0 0 1 0 1 1 1
42	1 0 0 1 0 1 0 0	106	1 0 0 1 0 1 1 0	170	1 0 0 1 0 1 0 1	234	1 0 0 1 0 1 1 1
43	0 1 0 1 0 1 0 0	107	0 1 0 1 0 1 1 0	171	0 1 0 1 0 1 0 1	235	0 1 0 1 0 1 1 1
44	1 1 0 1 0 1 0 0	108	1 1 0 1 0 1 1 0	172	1 1 0 1 0 1 0 1	236	1 1 0 1 0 1 1 1
45	0 0 1 1 0 1 0 0	109	0 0 1 1 0 1 1 0	173	0 0 1 1 0 1 0 1	237	0 0 1 1 0 1 1 1
46	1 0 1 1 0 1 0 0	110	1 0 1 1 0 1 1 0	174	1 0 1 1 0 1 0 1	238	1 0 1 1 0 1 1 1
47	0 1 1 1 0 1 0 0	111	0 1 1 1 0 1 1 0	175	0 1 1 1 0 1 0 1	239	0 1 1 1 0 1 1 1
48	1 1 1 1 0 1 0 0	112	1 1 1 1 0 1 1 0	176	1 1 1 1 0 1 0 1	240	1 1 1 1 0 1 1 1
49	0 0 0 0 1 1 0 0	113	0 0 0 0 1 1 1 0	177	0 0 0 0 1 1 0 1	241	0 0 0 0 1 1 1 1
50	1 0 0 0 1 1 0 0	114	1 0 0 0 1 1 1 0	178	1 0 0 0 1 1 0 1	242	1 0 0 0 1 1 1 1
51	0 1 0 0 1 1 0 0	115	0 1 0 0 1 1 1 0	179	0 1 0 0 1 1 0 1	243	0 1 0 0 1 1 1 1
52	1 1 0 0 1 1 0 0	116	1 1 0 0 1 1 1 0	180	1 1 0 0 1 1 0 1	244	1 1 0 0 1 1 1 1
53	0 0 1 0 1 1 0 0	117	0 0 1 0 1 1 1 0	181	0 0 1 0 1 1 0 1	245	0 0 1 0 1 1 1 1
54	1 0 1 0 1 1 0 0	118	1 0 1 0 1 1 1 0	182	1 0 1 0 1 1 0 1	246	1 0 1 0 1 1 1 1
55	0 1 1 0 1 1 0 0	119	0 1 1 0 1 1 1 0	183	0 1 1 0 1 1 0 1	247	0 1 1 0 1 1 1 1
56	1 1 1 0 1 1 0 0	120	1 1 1 0 1 1 1 0	184	1 1 1 0 1 1 0 1	248	1 1 1 0 1 1 1 1
57	0 0 0 1 1 1 0 0	121	0 0 0 1 1 1 1 0	185	0 0 0 1 1 1 0 1	249	0 0 0 1 1 1 1 1
58	1 0 0 1 1 1 0 0	122	1 0 0 1 1 1 1 0	186	1 0 0 1 1 1 0 1	250	1 0 0 1 1 1 1 1
59	0 1 0 1 1 1 0 0	123	0 1 0 1 1 1 1 0	187	0 1 0 1 1 1 0 1	251	0 1 0 1 1 1 1 1
60	1 1 0 1 1 1 0 0	124	1 1 0 1 1 1 1 0	188	1 1 0 1 1 1 0 1	252	1 1 0 1 1 1 1 1
61	0 0 1 1 1 1 0 0	125	0 0 1 1 1 1 1 0	189	0 0 1 1 1 1 0 1	253	0 0 1 1 1 1 1 1
62	1 0 1 1 1 1 0 0	126	1 0 1 1 1 1 1 0	190	1 0 1 1 1 1 0 1	254	1 0 1 1 1 1 1 1
63	0 1 1 1 1 1 0 0	127	0 1 1 1 1 1 1 0	191	0 1 1 1 1 1 0 1	255	0 1 1 1 1 1 1 1
64	1 1 1 1 1 1 0 0	128	1 1 1 1 1 1 1 0	192	1 1 1 1 1 1 0 1	256	1 1 1 1 1 1 1 1



Disposal of Electrical & Electronic Equipment (Applicable throughout the European Union and other European countries with separate collection programs)

This symbol, found on your product or on its packaging, indicates that this product should not be treated as household waste when you wish to dispose of it. Instead, it should be handed over to an applicable collection point for the recycling of electrical and electronic equipment. By ensuring this product is disposed of correctly, you will help prevent potential negative consequences to the environment and human health, which could otherwise be caused by inappropriate disposal of this product. The recycling of materials will help to conserve natural resources. For more detailed information about the recycling of this product, please contact your local city office, waste disposal service or the retail store where you purchased this product.

This document is property of SENECA srl. Duplication and reproduction are forbidden, if not authorized. Contents of the present documentation refers to products and technologies described in it. All technical data contained in the document may be modified without prior notice Content of this documentation is subject to periodical revision.



SENECA s.r.l.

Via Austria, 26 - 35127 - PADOVA - ITALY

Tel. +39.049.8705355 - 8705359 - Fax +39.049.8706287

e-mail: info@seneca.it - www.seneca.it